

## PSE-B552T06.02S

KNX Motion Detector 2.2 m TS 55, Secure, black matt



### Product functions:

- **KNX Data Secure**, integrated Bus coupler
- Suitable for 55 mm switch ranges e.g. MDT assortment 55 or GIRA E2 or BERKER B3, B7 or JUNG A 550 or Merten M-Pure
- **Motion detector with 2 sensors and brightness sensor**
- **Temperature sensor to measure the room temperature**
- **Activation sensitivity for day, night, and presence individually selectable**
- 2 Light channels, 1 HVC- and Alarm channel
- **Short-term presence to reduce the follow up time**
- Master/slave function, scenes and logic functions
- **Day/Night function**
- Blocking- and forced operation with release time
- External Push-button input for automatic and manual operation
- Recommended installation height: 2.20 m
- Installation in an installation box using the included installation frame

## Technical data:

<b>Device</b>	Device type	PSE Motion detector
	Article Number	PSE-B552T06.02S
	EAN / GTIN	4251916114107
	Colour	Black, matt finish
	Dimensions (H x W x D)	55 x 55 x 26 mm
	Weight, gross (incl. packaging)	0.087 kg
	Protection classification	IP20
	Installation type	Flush mounted
	Installation depth in switch box	12 mm
	Included carrying ring	Carrying ring A
	Recommended installation height	2.2 m
	Installation position	any
	Weight, net	0.054 kg
	<b>Inputs</b>	Number of sensors
Dynamic range		5 ... 1000 Lux
Range		10 m
Horizontal angle of coverage		170°
Adjustable sensitivity		10 steps
Measuring range for temperature		0 ... 40 °C
<b>KNX</b>	Nominal voltage KNX	30 V DC SELV
	Voltage range KNX	21 ... 31 V DC SELV
	Typical power consumption KNX bus	< 0,3 W
	KNX Medium	TP-256 with long frame support
	KNX Application	as of ETS 5 (latest)
	KNX Secure	KNX Data Secure
<b>Environmental conditions</b>	Ambient operating temperature	0 ... 45 °C
	Storage	-20 ... +55 °C
	Humidity	< 95 %
	Condensation permissible	No
<b>Connections</b>	Temperature sensor	Integrated
	KNX connection type	KNX terminal
	KNX cable cross section	0.6 ... 0.8 mm, solid conductor